

Many-body wave scattering by small bodies

A.G. Ramm

Mathematics Department, Kansas State University,
Manhattan, KS 66506-2602, USA

ramm@math.ksu.edu,

fax 785-532-0546, tel. 785-532-0580

<http://www.math.ksu.edu/~ramm>

Abstract

Scattering problem by several bodies, small in comparison with the wavelength, is reduced to linear algebraic systems of equations, in contrast to the usual reduction to some integral equations.

1 Introduction

Acoustic or electromagnetic (EM) wave scattering by one or several bodies is usually studied by reducing the problem to solving some integral equations. In this paper we show that if the bodies are small in comparison with the wavelength, then the scattering problem can be reduced to solving linear algebraic systems with matrices whose elements have physical meaning. These elements are electrical capacitances or elements of electric and magnetic polarizability tensors. The author has derived analytical explicit formulas allowing one to calculate these quantities for bodies of arbitrary shapes with arbitrary desired accuracy (see [1]).

We derive these linear algebraic systems and give formulas for the elements of the matrices of these systems. There is a large literature on wave scattering by small bodies, see [1] and references therein. The theory was originated by Lord Rayleigh [3], who understood that the main term in the scattered field is the dipole radiation if the body is small. Rayleigh did not give formulas for calculating the induced dipole moments for small bodies of arbitrary shapes. The dipole moments are uniquely defined by the

MSC: 35J10, 35P25, 74J20, 78A40, 78A45

PACS: 0340K, 4110H, 4320

key words: many-body scattering, acoustic wave scattering, electromagnetic wave scattering, numerical analysis

polarizability tensors. Therefore, the formulas, derived by the author (see [1]), allow one to calculate the dipole radiation for acoustic and EM wave scattering by small bodies of arbitrary shapes.

2 Acoustic wave scattering by small bodies

Let us start with acoustic wave scattering. Consider the problem

$$(\Delta + k^2)u = 0 \quad \text{in} \quad \mathbb{R}^3 \setminus \left(\bigcup_{m=1}^m D_m \right) \quad (1)$$

$$u|_{S_m} = 0, \quad 1 \leq m \leq M, \quad S_m := \partial D_m \quad (2)$$

$$u = u_0 + v, \quad (3)$$

$$\frac{\partial v}{\partial r} - ikv = o\left(\frac{1}{r}\right), \quad r := |x| \rightarrow \infty, \quad (4)$$

where Δ is the Laplacean, u_0 is an incident field which solves equation (1). Often, $u_0 = e^{ik\alpha \cdot x}$, where $\alpha \in S^2$ is a given vector and S^2 is the unit sphere.

Let us look for the solution of the form

$$u = u_0 + \sum_{m=1}^M \int_{S_m} g(x, s) \sigma_m(s) ds, \quad g(x, y) := \frac{e^{ik|x-y|}}{4\pi|x-y|}, \quad (5)$$

where σ_m , $1 \leq m \leq M$, are to be chosen so that the boundary conditions (2) hold. The function (5) satisfies (1) and (3)-(4) for any $\sigma_m \in L^2(S_m)$. The scattering amplitude is:

$$\mathcal{A}(\alpha', \alpha) = \lim_{|x| \rightarrow \infty, \frac{x}{|x|} = \alpha'} |x| e^{-ik|x|} v = \sum_{m=1}^M \frac{1}{4\pi} \int_{S_m} e^{-ik\alpha' \cdot s} \sigma_m ds, \quad \alpha' := \frac{x}{|x|}. \quad (6)$$

Let

$$a := \max_{1 \leq m \leq M} \text{diam } D_m,$$

and

$$d := \min_{m \neq j} \text{dist}(D_m, D_j).$$

We assume

$$ka \ll 1, \quad a \ll d. \quad (7)$$

Then

$$e^{-ik\alpha' \cdot (s-x_m)} \approx 1 \quad \text{if} \quad x_m \in D,$$

so

$$\mathcal{A}(\alpha', \alpha) = \sum_{m=1}^m \frac{e^{-ik\alpha' \cdot x_m}}{4\pi} \int_{S_m} \sigma_m ds := \sum_{m=1}^M \frac{Q_m}{4\pi} e^{-ik\alpha' \cdot x_m}, \quad Q_m := \int_{S_m} \sigma_m ds, \quad (8)$$

where $x_m \in D_m$ and α' is defined in (6). Since D_m is small, it does not matter which point x_m one takes in D_m . The Q_m plays the role of the total charge on the surface S_m .

If $\min_m |x - x_m| \gg a$ and $x_m \in D_m$, then

$$u(x) = u_0(x) + \sum_{m=1}^M \frac{e^{ik|x-x_m|}}{4\pi|x-x_m|} Q_m \left[1 + O\left(ka + \frac{a}{d}\right) \right]. \quad (9)$$

Let us derive a formula for Q_m . Using the boundary condition (2), one gets:

$$0 = u_0(s_m) + \sum_{j \neq m} g(s_m, x_j) Q_j + \int_{S_m} g(s_m, s) \sigma_m(s) ds, \quad (10)$$

where $s_m \in S_m$.

Since $ka \ll 1$, one has

$$g(s_m, s) = g_0(s_m, s) + O(ka),$$

where

$$g_0(s, t) := \frac{1}{4\pi|x-t|}.$$

Therefore equation (10) is the equation for the electrostatic charge distribution σ_m on the surface S_m of a perfect conductor D_m , charged to the potential

$$u_m := -u_0(s_m) - \sum_{j \neq m} g(s_m, x_j) Q_j.$$

The total charge on S_m is:

$$Q_m = C_m \mathcal{U}_m,$$

where C_m is the electrical capacitance of the conductor with the shape D_m . The total charge is defined as:

$$Q_m := \int_{S_m} \sigma_m ds.$$

Therefore, one gets:

$$Q_m = C_m \left(-u_0(s_m) - \sum_{j \neq m} g(s_m, x_j) Q_j \right), \quad 1 \leq m \leq M, \quad (11)$$

where C_m is the electrical capacitance of the perfect conductor with the boundary S_m .

Linear algebraic system (11) allows one to find Q_j , $1 \leq j \leq M$. If

$$\max_{1 \leq m \leq M} \sum_{j \neq m} \frac{C_m}{4\pi|s_m - x_j|} < 1, \quad (12)$$

then the matrix of the system (11) has diagonally dominant elements and, consequently, can be solved by iterations.

The approximate solution to the many-body scattering problem (1)–(4) is given by formula (9), where Q_m are determined from linear algebraic system (11).

Let us give a formula from [1] for the capacitance of a perfect conductor D with the boundary S . Denote the area of S by $|S|$. We assume that the conductor is placed in the medium with the dielectric permittivity $\varepsilon_0 = 1$. In this case the approximate formula for the capacitance is (see [1], p. 26):

$$C^{(n)} = 4\pi|S|^2 \left\{ \left(\frac{-1}{2\pi} \right)^n \int_S \int_S \frac{dsdt}{r_{st}} \underbrace{\int_S \dots \int_S}_{n \text{ times}} \psi(t, t_1) \dots \psi(t_{n-1}, t_n) dt_1 \dots dt_n \right\}^{-1}, \quad (13)$$

$$C^{(0)} = \frac{4\pi|S|^2}{J} \leq C, \quad J := \int_S \int_S \frac{dsdt}{r_{st}}, \quad r_{st} := |s - t|,$$

$$\psi(t, s) = \frac{\partial}{\partial N_t} \frac{1}{r_{st}},$$

and the error estimate of formula (13) is:

$$|C^{(n)} - C| = O(q^n), \quad 0 < q < 1, \quad (14)$$

where q depends on the geometry of S , and $n = 1, 2, 3, \dots$ is the approximation order.

If the boundary condition

$$u_N = \zeta u \quad \text{on} \quad S_m \quad (15)$$

is imposed in place of the Dirichlet condition (2), and ζ is the impedance, then C_m in (11) is replaced by

$$C_{m\zeta} := \frac{C_m}{1 + C_m(\zeta|S|)^{-1}}, \quad (16)$$

see [1], p. 97.

If

$$u_N|_{S_m} = 0, \quad 1 \leq m \leq M, \quad (17)$$

then the formula for the solution to problem (1), (17), (3), (4), is

$$u(x) = u_0(x) + \sum_{m=1}^M q(x, x_m) V_m \left[\Delta u(x_m) + \sum_{p,q=1}^M \beta_{pq,m} i k \frac{\partial u(x_m)}{\partial x_{m,q}} \frac{(x - x_m)_p}{|x - x_m|} \right], \quad (18)$$

where $(x - x_m)_p$ is the p -th coordinate of the vector $x - x_m$, $\frac{\partial}{\partial x_{m,q}}$ is the derivative with respect to the q -th coordinate of x calculated at the point x_m , and $\beta_{pq,m}$ is the magnetic polarizability tensor of D_m , defined by the formula ([1], p.98):

$$V_m \beta_{pq,m} = \int_S s_p \sigma(s) ds,$$

where V_m is the volume of D_m , the function σ solves the equation

$$\sigma = A\sigma - 2N_q,$$

N is the exterior unit normal to S_m , and

$$A\sigma = \int_{S_m} \frac{\partial}{\partial N} \frac{1}{2\pi r_{st}} \sigma(t) dt, \quad r_{st} = |s - t|.$$

The formulas for the tensor $\beta_{pq,m}$, analogous to the formulas (13)-(14) for the capacitance, are derived in [1, p.55, formula (5.15)]. The unknown quantities $\Delta u(x_m)$ and $\frac{\partial u(x_m)}{\partial x_q}$, $1 \leq m \leq M$, $1 \leq q \leq 3$, in (18) can be found from the following linear algebraic system, analogous to (11):

$$\Delta u(x_m) = \Delta u_0(x_m) - k^2 \sum_{j \neq m, j=1}^M g(x_m, x_j) V_j [\Delta u(x_j) + \sum_{p,q=1}^3 \beta_{pq,j} i k \frac{\partial u(x_j)}{\partial x_{j,q}} \frac{(x_m - x_j)_p}{|x_m - x_j|}] \quad (19)$$

$$\frac{\partial u(x_m)}{\partial x_{m,q}} = \frac{\partial u_0(x_m)}{\partial x_{m,q}} + \sum_{j \neq m, j=1}^M \frac{\partial g(x_m, x_j)}{\partial x_{m,q}} V_j [\Delta u(x_j) + \sum_{p,q=1}^3 \beta_{pq,j} i k \frac{\partial u(x_j)}{\partial x_{j,q}} \frac{(x_m - x_j)_p}{|x_m - x_j|}]. \quad (20)$$

In (19) we have used the equation

$$\Delta g(x, y) = -k^2 g(x, y),$$

which holds if $x \neq y$.

From the linear algebraic system (19)-(20) one finds the unknowns $\Delta u(x_m)$ and $\frac{\partial u(x_m)}{\partial x_{m,q}}$, $1 \leq m \leq M$, $1 \leq q \leq 3$.

If conditions (7) hold, then system (19)-(20) has a unique solution which can be obtained by iterations.

This completes the description of our method for solving many-body scattering problem for small bodies and acoustic (scalar) waves.

3 Electromagnetic wave scattering by small bodies

In the problem of electromagnetic (EM) wave scattering by many small bodies we assume

$$a \ll \lambda \ll d. \quad (21)$$

This assumption is more restrictive than (7). The reason is: in EM theory the fields are obtained by an application of first order differential operators, for instance $\nabla \times$, to potentials, such as the vector potential. Applying this operator and calculating the field in the far zone one neglects the term $|\frac{1}{x-x_m}|$ compared with the term k . This means that the following inequality is assumed:

$$\frac{1}{d} \ll \frac{1}{\lambda},$$

or

$$d \gg \lambda.$$

In the acoustic wave theory the potential itself $\int_S g(x, s) \sigma ds$ has physical meaning, it is the acoustic pressure, and this pressure is studied. Therefore, the condition $d \gg \lambda$ does not appear.

Condition (7) allows one to have many small particles on the distance of order λ , while condition (21), namely the inequality $d \gg \lambda$, does not allow this. Recall that d is the minimal distance between two neighboring particles. The formula for the scattering amplitude, analogous to (8), for EM wave scattering by small bodies is (see [2]):

$$A(\theta', \theta) = \frac{1}{4\pi} \sum_{m=1}^M \mathcal{S}_m \mathcal{U}_m e^{-ik\theta' \cdot x_m}. \quad (22)$$

Here $\mathcal{U} = \begin{pmatrix} E \\ H \end{pmatrix}$ is a 6-component vector, $\mathcal{S}_m$ is a 6x6 matrix, the scattering matrix, ε_0 and μ_0 are dielectrical and magnetic parameters of the medium, in which the body D_m is placed, and θ, θ' are the unit vectors in the direction of the incident and scattered waves, respectively. These vectors were denoted α and α' in Section 2. We have changed the notations because in EM theory α denotes the polarizability tensor.

The formula for $\mathcal{S}$ is (cf. [2])

$$\mathcal{S}_m \begin{pmatrix} E \\ H \end{pmatrix} = \frac{k^2 V_m}{4\pi} \begin{pmatrix} \alpha E - \theta'(\theta', \alpha E) & -\frac{\mu_0^{3/2}}{\varepsilon_0^{1/2}} [\theta', \tilde{\beta} H] \\ \left(\frac{\varepsilon_0}{\mu_0}\right)^{\frac{1}{2}} [\theta', \alpha E] & \mu_0 (\tilde{\beta} - \theta'(\theta', \tilde{\beta} H)) \end{pmatrix}. \quad (23)$$

Here V_m is the volume of D_m , α is the electric polarizability tensor of D_m , $\tilde{\beta}$ is the magnetic polarizability tensor of D_m . In [1, pp. 54–55] the author derives analytical formulas for calculation of the polarizability tensors α and β ,

$$\tilde{\beta} := \alpha(\tilde{\gamma}) + \beta, \quad \beta := \alpha_{ij}(-1), \quad \tilde{\gamma} := \frac{\mu - \mu_0}{\mu + \mu_0}, \quad \gamma := \frac{\varepsilon - \varepsilon_0}{\varepsilon + \varepsilon_0}. \quad (24)$$

Tensors β and $\tilde{\beta}$ are expressed through the polarizability tensor $\alpha = \alpha(\gamma)$. One has $\gamma = -1$ if $\varepsilon = 0$. Here $[\cdot, \cdot]$ is the vector product, $(\cdot, \cdot)$ is the scalar product.

The analytic formula from [1], p. 54, formula (5.9), for the tensor $\alpha = \alpha_{ij}(\gamma)$, $1 \leq i, j \leq 3$, that we referred to above, is analogous to formulas (13)–(14) for the electrical capacitance. The incident direction θ enters via the vectors E and H , which depend on θ . These vectors are calculated in formula (23) at the point x_m . The values of these vectors are determined from a linear algebraic system of equations. This system is derived similarly to the derivation of the systems (11) and (19)–(20). We do not write down this system since it would take much space, but the ideas are the same as the ones used in the derivations of (11) and (19)–(20).

4 Conclusions

In this paper it is shown how to reduce rigorously the many-body scattering problem to linear algebraic system in the case when the bodies are small in comparison with the wavelength. The theory is constructed for acoustic and EM wave scattering. The basic physical assumptions are (7) for acoustic scattering, and (21) for EM scattering.

References

- [1] Ramm, A. G. , **Wave scattering by small bodies of arbitrary shapes**, World Sci. Publishers, Singapore, 2005.
- [2] ———, Equations for the self-consistent field in random medium, Phys.Lett. A, 312, N3-4, (2003), 256-261.
- [3] Rayleigh, J. , **Scientific Papers**, Cambridge, 1922.